

# MC-2 Security Box Adapter



We've designed a custom adapter to fit your **MC-2 camera** into the original **Mini Cam Security Box**. Follow the steps below to install it properly:

**1. Disassemble the adapter.**



Separate the adapter pieces before installation.

**2. Insert the center “winged” piece. (See image below)**

Slide the middle piece with the wings into the bottom of the Security Box until it *snaps firmly into place*.

 **Note:** Once inserted, this piece cannot be removed without breaking it.

**3. Install the mounting bolt.**

Insert the bolt through the bottom of the Security Box and thread the backing nut from the inside.

Do **not** tighten yet.

**4. Mount the MC-2 camera. (See image below)**

Place the MC-2 camera into the Security Box and align it with the bolt. Tighten the screw into the camera's **1/4-20 thread** on the bottom.

**5. Secure the assembly. (See image below)**

Once the camera is tightened down, fully tighten the backing nut to lock the bolt securely in place.

